
pebbles

Design by Boris Klimek



bomma

Installation Manual
for Pendant Light Fixtures

Keep for later use!

Introduction

- Please read this user's manual carefully prior to installation and follow its instructions and recommendations.
- The installation of the pendant light requires more than one person.
- For safety reasons, as well as for warranty purposes, it is forbidden to use this product in breach of this manual and other purposes stipulated in this manual.
- Prior to assembly, use an appropriate circuit breaker to turn off electricity.
- All interventions regarding the wiring of the light fixture may only be carried out by a qualified electrician.
- Prevent children or persons with lowered sensory or psychological abilities from handling the light fixture, as it contains small and fragile pieces that could be dangerous when inappropriately handled or ingested.
- The producer bears no liability for damage caused by improper installation.
- The dimensions and weight of glass parts may differ slightly due to manual production.
- All Bomma products are made from hand-blown lead-free crystal. Any small bubbles, non-melts and inhomogeneities in the glass are not a reason for complaint. This is a characteristic feature of this traditional craft.
- Thanks to the manual process of blowing underlay glass, each piece is an original. Individual products may vary slightly in intensity, hue or even color. This is an accompanying characteristic of the underlay glass technology.
- The surface of the mounting may also include minor imperfections due to manual production.
- The Pebbles collection is inspired by natural stones, so the individual glasses may have an uneven color and a veined appearance.
- The pendant light is intended for interior lighting.

Components included in the package

- Hand-blown glass part (2x – 4x according to the type of the light fixture)
- Mounting
- Nonreplaceable light source
- Installation manual
- Gloves

Technical parameters, specifications

- Voltage rate: 110-240 V~, 50/60 Hz
- Protection: IP 20
- Input rate Pebbles S: 1 x LED module 17,5 W / Iout 350mA
- Input rate Pebbles L: 1 x LED module 29,4 W / Iout 1050mA
- Cable length: 2,5 m
- Weight Pebbles S: ~ 7,5 kg
- Size Pebbles S: dia. 300 mm, H 790 mm
- Weight Pebbles L: ~ 12 kg
- Size Pebbles L: dia. 300 mm, H 1180 mm
- Class: I.


1

Upon opening, first determine that there was no damage occurred during transport and that the light fixture is complete. Otherwise, please contact your seller immediately, as later claims may not be considered.


Assemble the lighting fixture according to the manual, recognizing that its installation wiring may only be carried out by a qualified electrician following general legal regulations.

Warning: Never unpack more than one light fixture at once to avoid mixing up components. If you have ordered several light fixtures of Pebbles, assemble individually each one at a time, and use only the components from that assembly. Glass, transformer, and mounting must not be interchanged!


Unscrew the nuts (4) and remove the canopy cover (5).




picture A




picture B






2

Unscrew the two screws and slide the transformer (7) out of the anchor plate (6).



3


Slip the anchor plate (6) on the incoming power supply cable from the ceiling and attach using appropriate screws and wall-plugs, which are not included in the package. Select their size and type according to the material of your ceiling and the weight of the light fixture.



download link
anchor plate drawing 1:1


4


Shorten the cable (9) from the mounting (2) to required length (100mm is used for connecting the cable inside the canopy).



5


Gradually slide the glass parts (1) onto the tube (2). Pay attention to the correct orientation of the glass! Both ends of the glass pieces have plastic rings glued on them. The ring with a groove must always be at the bottom.
It is not necessary to follow the order of shapes presented on our website www.bomma.cz. You can assemble the light fixture according to your imagination.






6


Thread the cable (9) through the upper end cap (3) and screw the end cap (3) into the thread at the end of the tube.



7


Thread the cable (9) through the canopy (5). Insert the steel string from the cable (9) into the reutlinger (8).
The string end must protrude on the upper side of the reutlinger at least 25 mm.
Attach the pull-out safety device (10) to the end of the string.






8

Slide the transformer (7) back into the original place on the anchor plate (6) and attach it with two screws.



9

Install the wiring according to the diagram.
Attention! Wrong connection can destroy both the transformer and the light source.



Input:
Brown = L
Blue = N
Yellow green = PE


Output:
Red = +
Black = -

10

Lift the canopy cover (5) and slide it onto the anchor plate so that the ends of the screws (11) are visible through the holes in the lower part. Attach the canopy cover by screwing the nuts (4) back onto the screws (11).

Congratulations! You may now reconnect the power and turn the light on.

When dismantling, first turn off the light and disconnect from the power supply. Then follow the above steps in reverse order. Use the original or similar packaging for possible later transport of the light fixture to prevent damage.



Maintenance

- When unpacking, assembling and cleaning the product, handle the individual parts with extra care, especially the glass parts which are very fragile.
- The assembly and wiring of the luminaire must be carried out by an authorized person.
- The pendant luminaire is intended for indoor use.
- We recommend consulting the suitability of the location and fixing of pendant luminaires to the ceiling material with a project manager, an engineer or other competent person.
- Do not cover the light source or touch the light source when the light is on.
- Do not make any repairs or changes to the components. Contact a specialist service center.
- Do not use any spare parts which have not been supplied or approved by the manufacturer.
- Do not expose the luminaire to an unsuitable environment where it might get damaged (water, heat, frost).
- Before servicing or cleaning pendant luminaires ensure sufficient access (ladder, scaffolding, mounting platform,...) so that you can reach and safely manipulate with the luminaire.
- **Warning:** the luminaire may in some parts have sharp edges which may cause injury. Take extra care when moving in close proximity to them.
- Any cleaning and maintenance should be carried out with the luminaire switched off and preferably disconnected (please mind this warning throughout the installation.)
- When changing a bulb, always disconnect the luminaire from the power supply.
- It is recommended to hang the luminaire at a sufficient height to avoid injury (such as head injury) to persons moving near the luminaire.
- It is recommended to install pendant luminaires in more than one person.
- After installing the luminaire, check that it is correctly and securely fixed to its base.
- Do not expose the luminaire to unreasonable loads, protect the luminaire from mechanical damage.
- The light source heats up during operation. Before starting any operation, wait until the light source cools down spontaneously _do not expose to rapid cooling_.
- When replacing the light source, use only the light source approved by the manufacturer (information about the type is on the label or in the installation instructions).
- Do not hang any other components on the luminaire in conflict with the manufacturer's installation instructions.
- Pay attention to checking all parts before their installation. Damaged components and glass parts _fragmentation, cracks_ can cause bodily injury to persons in their vicinity.
- Contact the manufacturer if a serious problem occurs during cleaning or maintenance of the luminaire.
- Any other manipulation with the luminaire should be carried out by qualified personnel or directly by the manufacturer.

Cleaning

- Any cleaning and maintenance should be carried out with the luminaire switched off and preferably disconnected.
- When cleaning, wear gloves. In particular, do not touch the plated crystal without gloves. This will prevent the formation of impressions, loss of luster and color.
- Use a soft duster to clean the metal parts. Metal parts can be cleaned with dry or dampened duster in lukewarm demineralized water. When cleaning the parts, do not under any circumstances use solvents, technical gasoline, technical cleaners, peroxides or alkalis. Avoid alcoholic agents, which could cause the change of surface color.
- Clean the stainless steel surfaces with special products, sold for this purpose.
- To clean the glass parts, use a mild cotton cloth, dry or moistened in lukewarm demineralized water, or a duster. Immediately after cleaning, dry the product completely so that no drops of water remain on the product, and carefully hang it back up.
- Take extra care when cleaning the individual parts of the luminaire that cannot be disconnected. Excessive handling might result in loosening or chipping.
- Do not use a dishwasher to wash any removable parts of the luminaire.

Important notice

- The manufacturer accepts no liability for damage resulting from improper installation, improper handling of the luminaire, including installation combined with accessories other than those recommended by the manufacturer.
- The manufacturer accepts no liability for damage resulting from unprofessional tampering with the fixings and safety features of the luminaire or for damage to the product caused by improper power supply voltage, storage or use of the luminaire in damp environment.
- Do not store the pendant luminaire in a damp environment, near a boiler, trap or other sources of steam. Do not place the luminaire over a bathtub in bathrooms and do not touch the luminaire if you are in contact with water.
- The manufacturer reserves the right to make minor variations in the design of the luminaire without prior notice.

Disposal

Upon the expiration of the product's shelf life, proceed in accordance to legal regulations for environmental protection and public health safety.

Waste Materials Catalog

Number	Category	Name
10 11 11*	N	Waste glass
		in small particles
		and glass powder
		containing heavy metals
10 11 12	O	Waste glass other than those
		mentioned in 10 11 11
17 04 01	O	Copper, bronze, brass
17 04 05	O	Iron and steel
20 01 01	O	Paper and cardboard
15 01 05	O	Composite packaging

Contact

BMRC GROUP s.r.o.
Pod dráhou 1638/7, Holešovice,
170 00 Praha 7
Czech Republic
+420 569 453 149
info@bomma.cz
www.bomma.cz

Instagram bomma_cz
Facebook bommacz

bomma.cz

drawn by	approved by	revision	date	signature
Karel Jankovský	Petr Novotný	3	5. 2025	

Control

Date of packaging

Notes

Notes

Notes

step beyond